

SLIM 1024

Wall mounted USB to DMX Stand Alone Device



SLIM stand Alone interface is the best controller for all indoor installations and projects which need an easy and user-friendly lighting control.

It can be easily wall mounted on any surface can fit to Europe and US wall plug standards.



CHROMATEQ



HARDWARE Options

DMX Output	2x512 or 1024 In/Out channels PC and Stand Alone
Multiple Zone	5 Zones, play up to 5 different scenes/sequences a time Stand Alone
Memory	Micro SD Card (all FAT format, up to 256 Gb) + Internal memory (No SD card required)
DMX Modes	DMX In/Out, Splitter DMX, merging DMX, DMX record, DMX trigger
Stand Alone Options	6 selectable modes: Buttons (8), Pages (10), Zones (5), Colour (99 RGB + 8 RGBW), Scene Speed, General dimmer. Time Clock setting adjustable in Stand Alone. 16 bits and fine channel management Automatic Scene Recovery if the power is cut off Cross Fade time between scenes Turn Off display after 4s., Default start scene, Dimmer and RGB color selection Master/Slave mode with Up to 32 devices combined and synchronized (64 universes)
Triggers (Stand Alone)	8 buttons with Blue status LED, 10 Pages Real Time Clock and calendar for each scene (hour, Day, Week, Month, Year) Can command the device from the Dry Contacts 5 Dry Contacts on 3-5V (On, On/Off, Release, Restart, Scene Priority, 32 contacts max) DMX input (DMX signal from another DMX device) Infrared Remote, Light intensity (with optional deported PCB and remote)
Max DMX outputs (USB)	x12 USB interfaces connected = 24 DMX max
Power	5V DC (USB), 5 to 24V. - 0.2A (screw connector), 0.2W, High Voltage Protection
Dimension	H: 1.9 cm ; W: 12.7 cm ; L: 11 cm ; 0.2 Kgs (WALL-MOUNTED)
Housing	Black or White housing, ABS Plastic
I/O Connectors	Mini USB 2.0, Screw Terminal block 2x9 Pins
Operating Temperature	-40 to +85 C°
IP Rating	IP40
Certifications	CE, LVD, RoHS
International Warranty	3 years



SOFTWARE Options

LED Player	Up to 64x512 DMX Outputs	FREE SOFTWARE Download and Update 
Pro DMX	30 mns Audio and Video Timeline	
Studio DMX	3D viewer in real time, Full mode	
Wi-Light APP	Software control (Android, iOS)	
Art-Net Output from PC	2x512 DMX Outputs per connected device	
System Compatibility	Windows, iOS, Linux	
Technical support	Worldwide, English, French, Chinese	

Contact, support, download from www.chromateq.com

PC minimum configuration:
Windows / Mac OS / Linux(Device)
2Ghz CPU, 8 Gb RAM
2Gb RAM graphic card
500 Mb disk
1 USB port (Device)
1 Ethernet port (ART-Net out/CQSA-E)

