Artist T4800 Artist T8800 Multi Channel Class D Amp



For Impedance Output





Artist T4800 and Artist T8800 professional power amplifier adopt switching power supply and class D circuit design which has good performance with high efficiency, light weight and good stability.

Two models are available, 4-channel Artist T4800 and 8-channel Artist T8800. It's 400W each channel at 8Ω. Each channel can work stably at 4Ω.

Artist T4800 and Artist T8800 adopt modular design. Two channels share one power supply system and amplification system. With elaborately selected components and state-of-the-art craftwork, Artist T4800 and Artist T8800 have very good fidelity and high damping factor. It's good choice for music reproduction, speech and AV system integration.

Artist T4800 4-Channel Class D Amp



Artist T8800

8-Channel Class D Amp



Artist T4800

Artist T8800

8Ω Mono	4x400W	8x400W	
4Ω Mono	4x800W	8x800W	
8Ω Bridge	2x1600W	4x1600W	
·	Mono, para	Mono, parallel, bridge	
nse(1W 8Ω stereo)	20Hz-20Ki	20Hz-20KHz(±0.5dB)	
	Mono Working Mode :32dB;	Mono Working Mode :32dB;Bridge Working Mode:38dB	
nnectors	Phoenix	Phoenix Socket	
Distortion(20Hz-20KHz, half power)	≤0.0≥	≤0.05%	
istortion(20Hz-20KHz, half power)	≥0.0≥	≤0.05%	
	Clas	Class D	
ion(1/8RMS/230V)	1.3A	2.5A	
	2	2U	
×D)	483×88	483×88×450mm	
	8.5Kg	11.5Kg	
	4Ω Mono 8Ω Bridge Inse(1W 8Ω stereo) Innectors Distortion(20Hz-20KHz, half power) istortion(20Hz-20KHz, half power) ion(1/8RMS/230V)	4Ω Mono 8Ω Bridge 2x1600W Mono, para sinse(1W 8Ω stereo) Mono Working Mode :32dB; nectors Phoenis Distortion(20Hz-20KHz, half power) istortion(20Hz-20KHz, half power) Class ion(1/8RMS/230V) 1.3A 2 ×D)	